

**Tabla de Compatibilidad**

Clavija	Tensión de Salida	Medidas Conector	Compatibilidad
M1	15V	ø6.3*3.0*10.7mm	TOSHIBA:15V/3A,15V/4A,15V/5A,15V/6A,15V/8A;NEC:15V/6A etc.
M3	16V	ø6.0*4.3*10.7mm pin1.0	SONY:16V/3.42A,16V/3.75A,16V/4A; FUJITSU:16V/3.36A,16V/3.75A etc.
M4	18,5V	ø4.8*1.7*10.7mm DC-F	HP/COMPAQ:18.5V/2.7A,18.5V/3.5A,18.5V/3.8A,18.5V/4.9A
			DELTA:19V/2.64A;ASUS:19V/2.64A;NEC:19V/2.64A etc.
M5	19V	ø5.5*2.5*10.7mm DC-F	IBM:19V/4.2A;DELL:19V/3.16A,19V/3.42A;COMPAQ/HP:18.5V/4.9A,19V/4.9A
			DELTA:19V/2.64A,19V/4.5A;ASUS:19V/4.74A;LS:20V/3.25A;
			TOSHIBA:19V/3.16A,19V/3.42A,19V/4.74A; NEC:19V/2.64A,19V/3.16A
			LITEON:19V/3.16A,19V/3.42A,19V/3.95A,19V/4.74A;
			GATEWAY:19V/3.16A,19V/3.42A,19V/3.68A,19V/4.74A, etc.
M6	19V	ø5.5*3.0*10.7mm pin1.0	SAMSUNG:19V/3.16A,19V/3.75A,19V/4.22A,19V/4.74A etc.
M7	19V	ø5.5*2.1*10.7mm DC-F	ACER:19V/3.16A,19V/3.42A,19V/4.74A;LITEON:19V/3.16A,19V/3.42A;NEC:19V/3.16A etc.
M8	19,5V	ø6.0*4.3*10.7mm pin1.0	SONY:19.5V/2.7A,19.5V/3A,19.5V/4.1A, 19.5V/4.6A;
			FUJITSU:19V/3.16A,19V/3.69A,19V/4.22A etc.
M9	19,5V Chip	7.4*5.0*12mm	DELL:19.5V/3.34A,19.5V/4.62A etc
M12	18,5V	ø7.4*5.5*12mm	HP/Compaq: 18.5V3.5A/4.9Aor19V 4.74A
M28	20V	Rectangular	Lenovo:20V 2.25A ;20V 3.25A;20V 4.5A etc.
M29	19,5V	ø4.5*3.0*12mm	HP Envy:19.5V/4.62A; 19.5V/2.31A etc.
M30	19,5V	ø4.8*1.7*12mm	HP Envy:19.5V/3.33A ; 19.5V/4.7A etc.